

# PRODUCT DATASHEET

## SMART+ ZB NIGHTLIGHT PLUG EU

SMART+ Nightlight plug | Nightlight integrated plug with smart socket to control non smart devices with ZigBee technology



### Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems
- Nightlight as an orientation light or safety light for children's rooms, stairs, or bedrooms

### Product benefits

- Integrates conventional electric equipment into compatible smart home systems
- Nightlight as an orientation light or safety light at night or in dark area
- Simple connection of electric devices via standard socket
- Enables switching of conventional light sources and other electric devices

### Product features

- Control via compatible smart home system, or on/off button on the device
- Control via voice control available: Google Assistant or Amazon Alexa, depending on the smart home system in use
- Functionality depends on used type of control
- High switching power: up to 3,680 W / 16 A
- Network protocol: ZigBee 3.0
- Nightlight integrated with warm white, not dimmable
- Scheduling




TECHNICAL DATA

Electrical data

Nominal voltage	230 V
Mains frequency	50 Hz

Dimensions & Weight



Product weight	120.00 g
Length	60 mm
Width	60 mm
Height	84 mm

Lifespan

Number of switching cycles	100000
----------------------------	--------

Colors & materials

Product color	White
Body material	Plastic

Temperatures & operating conditions

Ambient temperature range	-10...+35 °C
---------------------------	--------------

Capabilities

Compatible smart home technology	Philips Hue / Amazon Alexa / Google Assistant
----------------------------------	---

Certificates & Standards

Protection class	I
Type of protection	IP20



EQUIPMENT / ACCESSORIES

- Control via app requires a compatible Smart home system

## Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Plug, after use in order to avoid them being accidentally switched on.
- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Plug in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (max. 16 A).
- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.

## DOWNLOAD DATA

Documents and certificates	Document name
 Extended installation guide	SMART+ ZIGBEE INSTALLATION GUIDE
 Declarations of conformity	EU Declaration of Conformity – Smart Zigbee Nightlight Plug EU_AC31262

## LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075570955	Folding box 1	61 mm x 96 mm x 154 mm	188.00 g	0.90 dm <sup>3</sup>
4058075570962	Shipping box 4	211 mm x 167 mm x 141 mm	883.00 g	4.97 dm <sup>3</sup>

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

## DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.