

# PRODUCT DATASHEET

## SMART+ Wifi Trunk SQ Wall 80cm RGB + W

Smart+ Trunk Pathway Multicolor | Outdoor Smart Trunk Square Pathway



### Areas of application

- General illumination
- Outdoor use (IP44)
- Gardens
- Patios, balconies

### Product benefits

- Easy and quick installation
- Colorful garden lighting with smart and intelligent control options
- High-quality materials
- Uses multi color and cold or warm white light for most flexible lighting scenes
- Combines the functionality of general lighting and mood lighting

### Product features

- Controllable via LEDVANCE SMART+ App (with minimum Android 8.0 or iOS 14.0)
- Controllable via voice control available: Google Assistant or Amazon Alexa
- RGB color control
- Dimmable
- Color temperature: 3,000 K (Warm White)
- Network protocol: WiFi
- Type of protection: IP44



## TECHNICAL DATA

### Electrical data

Nominal wattage	7.50 W
Nominal voltage	220...240 V
Mains frequency	50...60 Hz
Nominal current	50.000 mA
Power factor $\lambda$	> 0.60
Protection class	I

### Photometrical data

Luminous flux	180 lm
Total luminous flux of contained light sources	550 lm
Luminous efficacy	24 lm/W
Color temperature	3000 K
Light color (designation)	Warm White / RGB
Color rendering index Ra	$\geq 80$
Standard deviation of color matching	$\leq 6$ sdcn
Flickering metric (Pst LM)	-
Stroboscope effect metric (SVM)	-
Photobiological safety group acc. to EN62778	RG0
Beam angle	75 °

### Dimensions & Weight

Length	66.00 mm
Width	66.00 mm
Height	800.00 mm
Product weight	1425.00 g



SMART OUTD WIFI TRUNK SQ  
80CM RGBW

### Materials & Colors

Product color	Wood decor
Housing color	Wood decor
Body material	Aluminum
Glow Wire Test according to IEC 60695-2-12	650 °C
Mercury content	0.0 mg

### Application & Mounting

Ambient temperature range	-20...+40 °C
Type of connection	Terminal, 3-Pole (L, N, PE)
Type of protection	IP44
Dimmable	Yes
Type of dimming	WiFi
Mounting type	Standing
Application environment	Outdoor
With light source	Yes

### Lifespan

Lifespan L70/B50 at 25 °C	25000 h
Number of switching cycles	12500

### Certificates & Standards

Standards	CE / UKCA
Ball shot safe	No
Replaceable light source (EPREL)	Not replaceable

### Additional product data

Product remark	Reset settings to default by switching the product on for three seconds and off for three seconds and repeating this five times.
----------------	--

## EQUIPMENT / ACCESSORIES





- For control via LEDVANCE SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)
- Control via app or voice control requires compatible Smart home system
- Mounting screws and dowels included
- Power supply included

### Safety advice

- All electrical connections must be made by a qualified person.
- Caution, risk of electric shock.

- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.
- Check wall-ceiling for suitability. If uncertain, seek professional advice.

**DOWNLOAD DATA**

Documents and certificates		Document name
	User instruction / safety instructions	SMART OUTD WIFI TRUNK SQ
	Declarations of conformity	SMART OUTD WIFI RGBW
	Declarations of conformity UKCA	SMART OUTD WIFI RGBW
	Declarations of conformity UKCA	SMART OUTD WIFI

**LOGISTICAL DATA**

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075763388	Folding box 1	85 mm x 85 mm x 820 mm	1591.00 g	5.92 dm <sup>3</sup>
4058075763395	Shipping box 2	840 mm x 190 mm x 105 mm	3633.00 g	16.76 dm <sup>3</sup>

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

**References / Links**

- Further information and frequently asked questions (FAQs) at [www.ledvance.com/consumer/smart/faq](http://www.ledvance.com/consumer/smart/faq)

**DISCLAIMER**

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.