

PRODUCT DATASHEET

DULUX L 36 W/840 2G11

OSRAM DULUX® L LUMILUX® | CFLni, with 4-pin 2G11 base for ECG/CCG operation



Areas of application

- Offices, public buildings
- Shops
- Supermarkets and department stores
- Hotels, restaurants
- Industry

Product benefits

- Less than half as long as tubular fluorescent lamps

Product features

- Short and compact pin-base lamp with double-turn tubes
- Single-ended four-pin plug-in 2G11 base
- Dimmable (1...100 % with QUICKTRONIC® QT_i DALI/DIM)
- Good color rendering index



TECHNICAL DATA


Electrical data

Nominal wattage	36 W
Construction wattage	36.00 W
Nominal voltage	220 V

Photometrical data

Luminous flux at 25 °C	2900 lm
Color rendering index Ra	80...89
Light color	8

Dimensions & Weight



Overall length	411.00 mm
Diameter	17.50 mm
Product weight	114.00 g

Additional product data

Base (standard designation)	2G11
Mercury content	3.0 mg

Country-specific categorizations

Order reference	DULUX L 36W/840
-----------------	-----------------

Energy labelling regulation data acc EU 2019/2015

Light source cap-type (or other electric interface)	2G11
Length	411.00 mm
Height	17.50 mm
Width	17.50 mm

EQUIPMENT / ACCESSORIES

- Suitable for standard control gears and starters
- Suitable for operation on electronic and conventional control gear

Safety advice

- In case of lamp breakage: www.ledvance.com/brokenlamp

DOWNLOAD DATA

Documents and certificates		Document name
	User instruction / safety instructions	334200_Technical guide - OSRAM DULUX pin-base

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4050300903859	Folding box 1	45 mm x 25 mm x 440 mm	156.00 g	0.50 dm ³
4008321202048	Shipping box 50	266 mm x 246 mm x 454 mm	8260.00 g	29.71 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

- For more information on the system guarantee and the terms and conditions of the guarantee visit www.ledvance.com/system-guarantee

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.