

PRODUCT DATASHEET LINK SENSOR PIR 40FT 3.5mm BLE WH

LEDVANCE LINK™ PLUG AND PLAY MOTION SENSOR | LEDVANCE LINK Plug and Play Motion Sensors



Product features

- Commission and configure with LEDVANCE LINK™ app
- Control using either the LEDVANCE LINK $^{\mbox{\tiny TM}}$ app or the wireless controller
- Grouping and Zoning: Wirelessly group luminaires to act in sync with each other
- Scene Control: Preset various scenes for individual or group of luminaires using the app and/or wireless/wired controllers
- QR Code for Admin/Guest control: Using the LEDVANCE LINK™ app, Admin and Guest QR codes for each zone can be generated. Allows copying the settings to another phone/tablet by scanning this QR code
- Allows setting time-based schedules and high-end and low-end trim through the LEDVANCE LINK™ app

TECHNICAL DATA

Electrical data

Nominal wattage	0.45 W
Nominal voltage	12 V
Mains frequency	35 Hz

Dimensions & Weight

Length	59.94 mm
Width	66.29 mm
Height	59.94 mm
Product weight	48.00 g

Additional product data

Capabilities

Dimmable	Yes

Certificates & Standards

Protection class	N
Type of protection	IP66

DOWNLOAD DATA

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
0046135626340	Folding box	70 mm x 70 mm x 65 mm	60.00 g	0.32 dm ³
4058075777170	Shipping box 100	370 mm x 370 mm x 280 mm	6475.00 g	38.33 dm³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.