


PRODUCT DATASHEET

LINK BOOSTER 6A BLE

LEDVANCE LINK™ SIGNAL BOOSTER | LEDVANCE LINK Signal Boosters



Product features

- Commission and configure with LEDVANCE LINK™ app
- Control using either the LEDVANCE LINK™ app or the wireless controller
- Grouping and Zoning: Wirelessly group luminaires to act in sync with each other
- Scene Control: Preset various scenes for individual or group of luminaires using the app and/or wireless/wired controllers
- QR Code for Admin/Guest control: Using the LEDVANCE LINK™ app, Admin and Guest QR codes for each zone can be generated. Allows copying the settings to another phone/tablet by scanning this QR code
- Allows setting time-based schedules and high-end and low-end trim through the LEDVANCE LINK™ app

TECHNICAL DATA

Dimensions & Weight

Product weight	226.8 g
----------------	---------

Additional product data

NAED	63653
------	-------

DOWNLOAD DATA

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
0046135636530	Folding box 1	61 mm x 36 mm x 201 mm	272.00 g	0.44 dm ³
4099854140907	Shipping box 100	415 mm x 385 mm x 325 mm	27635.00 g	51.93 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.